


Pagoda-2 / Pagoda-2B

D1 = 3.65 mm
D2 = 10.45 mm

All dimensions are ± 0.1 mm.
The use of the provided assembly jig is highly recommended to meet these tolerances.
Even small inaccuracies can result in a significant shift in center frequency and reduction of axial ratio.

Pagoda-3 / Pagoda-3B

	5.3 GHz	5.4 GHz	5.5 GHz	5.6 GHz	5.7 GHz	5.8 GHz	5.9 GHz	6.0 GHz
D1	4.39 mm	4.24 mm	4.10 mm	3.95 mm	3.80 mm	3.65 mm	3.51 mm	3.36 mm
D2	11.63 mm	11.40 mm	11.16 mm	10.92 mm	10.69 mm	10.45 mm	10.21 mm	9.98 mm